

Time = 0

Instruction Status				
Instruction	Issue Inst	Read Operands	Execute Inst	Write Result
LF F6,34(R2)	X			
LF F2,34(R3)				
MULTF F0,F2,F4				
SUBF F8,F6,F2				
DIVF F10,F0,F6				
ADDF F6,F8,F2				

Time = 2,3

Instruction Status				
Instruction	Issue Inst	Read Operands	Execute Inst	Write Result
LF F6,34(R2)	x	x		
LF F2,34(R3)				
MULTF F0,F2,F4				
SUBF F8,F6,F2				
DIVF F10,F0,F6				
ADDF F6,F8,F2				

Functional Unit Status

FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS	Yes	Load	F6	R2					
2	Mult1									
3	Mult2									
4	Add									
5	Div									

Functional Unit Status

FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS	Yes	Load	F6	R2					
2	Mult1									
3	Mult2									
4	Add									
5	Div									

Register Result Status

FU#	F0	F2	F4	F6	F8	F10	12	...	F30
				1					

Register Result Status

FU#	F0	F2	F4	F6	F8	F10	12	...	F30
							1		

Time = 1

Instruction Status				
Instruction	Issue Inst	Read Operands	Execute Inst	Write Result
LF F6,34(R2)	x	x		
LF F2,34(R3)				
MULTF F0,F2,F4				
SUBF F8,F6,F2				
DIVF F10,F0,F6				
ADDF F6,F8,F2				

Time = 4

Instruction Status				
Instruction	Issue Inst	Read Operands	Execute Inst	Write Result
LF F6,34(R2)	x	x	x	x
LF F2,34(R3)			x	
MULTF F0,F2,F4				
SUBF F8,F6,F2				
DIVF F10,F0,F6				
ADDF F6,F8,F2				

Functional Unit Status

FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS	Yes	Load	F6	R2					
2	Mult1									
3	Mult2									
4	Add									
5	Div									

Functional Unit Status

FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS	Yes	Load	F2	R3					
2	Mult1									
3	Mult2									
4	Add									
5	Div									

Register Result Status

FU#	F0	F2	F4	F6	F8	F10	12	...	F30
				1					

Register Result Status

FU#	F0	F2	F4	F6	F8	F10	12	...	F30
							1		

Time = 5

Instruction Status					
Instruction		Issue Inst	Read Operands	Execute Inst	Write Result
LF	F6,34(R2)	x	x	x	x
LF	F2,34(R3)	x	X		
MULTF	F0,F2,F4		X		
SUBF	F8,F6,F2				
DIVF	F10,F0,F6				
ADDF	F6,F8,F2				

Time = 7

Instruction Status					
Instruction		Issue Inst	Read Operands	Execute Inst	Write Result
LF	F6,34(R2)	x	x	x	x
LF	F2,34(R3)	x	x		
MULTF	F0,F2,F4		x		
SUBF	F8,F6,F2		x		
DIVF	F10,F0,F6		X		
ADDF	F6,F8,F2				

Functional Unit Status

FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS	Yes	Load	F2	R3					
2	Mult1	Yes	Mult	F0	F2	F4	1		No	Yes
3	Mult2									
4	Add									
5	Div									

Functional Unit Status

FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS	Yes	Load	F2	R3					
2	Mult1	Yes	Mult	F0	F2	F4	1		No	Yes
3	Mult2									
4	Add	Yes	Sub	F8	F6	F2		1	Yes	No
5	Div	Yes	Div	F10	F0	F6	2		No	Yes

Register Result Status

FU#	F0	F2	F4	F6	F8	F10	12	...	F30
FU#	2	1							

Register Result Status

FU#	F0	F2	F4	F6	F8	F10	12	...	F30
FU#	2	1			4	5			

Time = 6

Instruction Status					
Instruction		Issue Inst	Read Operands	Execute Inst	Write Result
LF	F6,34(R2)	x	x	x	x
LF	F2,34(R3)	x	x		
MULTF	F0,F2,F4		x		
SUBF	F8,F6,F2		X		
DIVF	F10,F0,F6				
ADDF	F6,F8,F2				

Time = 8

Instruction Status					
Instruction		Issue Inst	Read Operands	Execute Inst	Write Result
LF	F6,34(R2)	x	x	x	x
LF	F2,34(R3)	x	x	X	X
MULTF	F0,F2,F4		x		
SUBF	F8,F6,F2		x		
DIVF	F10,F0,F6		x		
ADDF	F6,F8,F2				

Functional Unit Status

FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS	Yes	Load	F2	R3					
2	Mult1	Yes	Mult	F0	F2	F4	1		No	Yes
3	Mult2									
4	Add	Yes	Sub	F8	F6	F2	1	Yes	Yes	
5	Div									

Functional Unit Status

FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS	No								
2	Mult1	Yes	Mult	F0	F2	F4	1		Yes	Yes
3	Mult2									
4	Add	Yes	Sub	F8	F6	F2	1	Yes	Yes	
5	Div	Yes	Div	F10	F0	F6	2		No	Yes

Register Result Status

FU#	F0	F2	F4	F6	F8	F10	12	...	F30
FU#	2	1			4				

Register Result Status

FU#	F0	F2	F4	F6	F8	F10	12	...	F30
FU#	2				4	5			

Time = 9; Mult Given Priority on Read

		Instruction Status			
Instruction		Issue Inst	Read Operands	Execute Inst	Write Result
LF	F6,34(R2)	x	x	x	x
LF	F2,34(R3)	x	x	x	x
MULTF	F0,F2,F4	x	X		
SUBF	F8,F6,F2	x			
DIVF	F10,F0,F6	x			
ADDF	F6,F8,F2				

Time = 11,12

		Instruction Status			
Instruction		Issue Inst	Read Operands	Execute Inst	Write Result
LF	F6,34(R2)	x	x	x	x
LF	F2,34(R3)	x	x	x	x
MULTF	F0,F2,F4	x	x		
SUBF	F8,F6,F2	x		x	
DIVF	F10,F0,F6	x			
ADDF	F6,F8,F2				

Functional Unit Status										
FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS	No								
2	Mult1	Yes	Mult	F0	F2	F4				
3	Mult2									
4	Add	Yes	Sub	F8	F6	F2	1	Yes	Yes	
5	Div	Yes	Div	F10	F0	F6	2	No	Yes	

Register Result Status										
F0	F2	F4	F6	F8	F10	12	...	F30		
FU#	2			4	5					

Time = 10; Sub Reads F2

		Instruction Status			
Instruction		Issue Inst	Read Operands	Execute Inst	Write Result
LF	F6,34(R2)	x	x	x	x
LF	F2,34(R3)	x	x	x	x
MULTF	F0,F2,F4	x	x		
SUBF	F8,F6,F2	x	X		
DIVF	F10,F0,F6	x			
ADDF	F6,F8,F2				

Time = 13

		Instruction Status			
Instruction		Issue Inst	Read Operands	Execute Inst	Write Result
LF	F6,34(R2)	x	x	x	x
LF	F2,34(R3)	x	x	x	x
MULTF	F0,F2,F4	x	x		
SUBF	F8,F6,F2	x	x		X X
DIVF	F10,F0,F6	x			
ADDF	F6,F8,F2	X			

Functional Unit Status										
FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS	No								
2	Mult1	Yes	Mult	F0	F2	F4				
3	Mult2									
4	Add	Yes	Sub	F8	F6	F2				
5	Div	Yes	Div	F10	F0	F6	2	No	Yes	

Register Result Status										
F0	F2	F4	F6	F8	F10	12	...	F30		
FU#	2			4	5					

Time = 14

Instruction Status				
Instruction	Issue Inst	Read Operands	Execute Inst	Write Result
LF F6,34(R2)	x	x	x	x
LF F2,34(R3)	x	x	x	x
MULTF F0,F2,F4	x	x		
SUBF F8,F6,F2	x	x	x	x
DIVF F10,F0,F6	x			
ADDF F6,F8,F2	x	X		

Time = 17

Instruction Status				
Instruction	Issue Inst	Read Operands	Execute Inst	Write Result
LF F6,34(R2)	x	x	x	x
LF F2,34(R3)	x	x	x	x
MULTF F0,F2,F4	x	x		
SUBF F8,F6,F2	x	x	x	x
DIVF F10,F0,F6	x			
ADDF F6,F8,F2	x	x		X

Functional Unit Status

FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS									
2	Mult1	Yes	Mult	F0	F2	F4				
3	Mult2									
4	Add	Yes	Add	F6	F8	F2				
5	Div	Yes	Div	F10	F0	F6	2		No	Yes

Register Result Status

FU#		F0	F2	F4	F6	F8	F10	12	...	F30
		2		4		5				

Time = 15,16

Instruction Status				
Instruction	Issue Inst	Read Operands	Execute Inst	Write Result
LF F6,34(R2)	x	x	x	x
LF F2,34(R3)	x	x	x	x
MULTF F0,F2,F4	x	x		
SUBF F8,F6,F2	x	x	x	x
DIVF F10,F0,F6	x			
ADDF F6,F8,F2	x	x		

Time = 18,19

Instruction Status				
Instruction	Issue Inst	Read Operands	Execute Inst	Write Result
LF F6,34(R2)	x	x	x	x
LF F2,34(R3)	x	x	x	x
MULTF F0,F2,F4	x	x		
SUBF F8,F6,F2	x	x	x	x
DIVF F10,F0,F6	x			
ADDF F6,F8,F2	x	x		x

Functional Unit Status

FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS									
2	Mult1	Yes	Mult	F0	F2	F4				
3	Mult2									
4	Add	Yes	Add	F6	F8	F2				
5	Div	Yes	Div	F10	F0	F6	2		No	Yes

Register Result Status

FU#		F0	F2	F4	F6	F8	F10	12	...	F30
		2		4		5				

Functional Unit Status

FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS									
2	Mult1	Yes	Mult	F0	F2	F4				
3	Mult2									
4	Add	Yes	Add	F6	F8	F2				
5	Div	Yes	Div	F10	F0	F6	2		No	Yes

Register Result Status

FU#		F0	F2	F4	F6	F8	F10	12	...	F30
		2		4		5				

Time = 20

Instruction Status				
Instruction	Issue	Read	Execute	Write
	Inst	Operands	Inst	Result
LF F6,34(R2)	x	x	x	x
LF F2,34(R3)	x	x	x	x
MULTF F0,F2,F4	x	x	X	X
SUBF F8,F6,F2	x	x	x	x
DIVF F10,F0,F6	x			
ADDF F6,F8,F2	x	x	x	

Functional Unit Status										
FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS									
2	Mult1	No								
3	Mult2									
4	Add	Yes	Add	F6	F8	F2				
5	Div	Yes	Div	F10	F0	F6	2		Yes	Yes

Register Result Status								
F0	F2	F4	F6	F8	F10	12	...	F30
FU#			4		5			

Time = 21; 40 Cycles Until Div Finishes

Instruction Status				
Instruction	Issue	Read	Execute	Write
	Inst	Operands	Inst	Result
LF F6,34(R2)	x	x	x	x
LF F2,34(R3)	x	x	x	x
MULTF F0,F2,F4	x	x	x	x
SUBF F8,F6,F2	x	x	x	x
DIVF F10,F0,F6	x	X		
ADDF F6,F8,F2	x	x	x	X

Functional Unit Status										
FU	Name	Busy	Fm	Fi	Fj	Fk	Qj	Qk	Rj	Rk
1	Int/LS									
2	Mult1									
3	Mult2									
4	Add	No								
5	Div	Yes	Div	F10	F0	F6				

Register Result Status								
F0	F2	F4	F6	F8	F10	12	...	F30
FU#					5			